

**WHAT IS CLAIMED IS:**

1. An active pixel image sensor comprised of a plurality of pixels, at least one pixel comprising
  - a photodetector,
  - a transistor,
  - a charge to voltage conversion region coupled to said photodetector and connected to the input of said transistor; and
  - a capacitor connected in parallel with the charge to voltage conversion region wherein the capacitor is designed to have a low voltage coefficient.
2. The device in claim 1, wherein said capacitor provides a capacitance independently of a voltage on said charge to voltage conversion node
3. The device in claim 1, wherein said capacitor comprises a polysilicon to polysilicon double plate capacitor
4. The device in claim 1, wherein said capacitor comprises a polysilicon to metal interconnect double plate capacitor
5. The device in claim 1, wherein said capacitor comprises a metal interconnect to metal interconnect double plate capacitor
6. An active pixel image sensor comprised of a plurality of pixels, at least one pixel comprising
  - a photodetector,
  - a transistor,
  - said photodetector also operating as a charge to voltage conversion region connected to the input of said transistor; and

a capacitor connected in parallel with photodetector wherein the capacitor is designed to have a low voltage coefficient

7. The device in claim 6, wherein said capacitor provides a capacitance independently of a voltage on said charge to voltage conversion node

8. The device in claim 6, wherein said capacitor comprises a polysilicon to polysilicon double plate capacitor

9. The device in claim 6, wherein said capacitor comprises a polysilicon to metal interconnect double plate capacitor.

10. The device in claim 6, wherein said capacitor comprises a metal interconnect to metal interconnect double plate capacitor

11. An active pixel image sensor comprised of a plurality of pixels, at least one pixel comprising  
a photodetector,  
a transistor,  
a charge to voltage conversion region coupled to said photodetector and connected to the input of said transistor; and  
wherein said transistor is configured to operate as a common source amplifier

12. An active pixel image sensor comprised of a plurality of pixels, at least one pixel comprising  
a photodetector,  
a transistor,  
a charge to voltage conversion region coupled to said photodetector and connected to the input of said transistor.

wherein said transistor is configured to operate as a common source amplifier, and

a capacitor connected in parallel with the charge to voltage conversion region wherein the capacitor is designed to have a low voltage coefficient.